

2 Port ExpressCard 1394b FireWire Laptop Adapter Card

StarTech ID: EC1394B2



This 2 Port ExpressCard FireWire Adapter Card adds two 1394b FireWire ports to a laptop computer, providing a cost-effective way to add IEEE 1394A and IEEE 1394B FireWire devices even if the laptop doesn't have a built-in FireWire 400 or FireWire 800 port.

Simply insert the IEEE 1394B FireWire 800 card (EC1394B2) into an ExpressCard slot, and you'll be able to connect a broad range of FireWire devices to your laptop, while relying on data transfer speeds of up to 800Mbps.

Plus, the card is backward compatible with 1394a devices, so you can connect both FireWire 400 and 800 devices to the notebook, using the same adapter.

Applications and Solutions

- Digital cameras
- DVD drives
- External CDR-CDRW drives
- iPods/MP3 players
- Portable hard drives
- Printers
- Scanners

Features

- Experience the power and speed of FireWire 800 and ExpressCard
- Hot swap capabilities allow you to connect or disconnect devices without turning off the host computer
- Supports data transfer rates of up to 100, 200, 400 and 800 Mbps
- Supports various types of FireWire 800 (1394B) and 1394A standards

Technical Specifications

- Warranty: Lifetime warranty
- Bus Type: 34mm ExpressCard
- Connector Types: 2 - FireWire 800 9 pin Female
- Product Height: 0.79 in [20 mm]
- Product Length: 4.72 in [120 mm]
- Maximum Data Transfer Rate: 800 Mbps
- Number of Ports: 2
- Carton Quantity: 40
- Shipping (Package) Weight: 0.27 lb [0.12 kg]
- Product Weight: 1.06 oz [30 g]
- Product Width: 1.34 in [34 mm]
- System Requirements: One available ExpressCard Slot
- Power Adapter Included: No
- Optional Power Adapter: 12VDC, 2000+ mA, center positive, type H plug
- Chipset ID: TI - XIO2213A
- OS Compatibility: Windows 2000/ XP(32/64bit)/ Vista(32/64bit)/ 7(32/64bit), Mac OS 10.5.x and up, and Linux

