

3 Port CardBus 1394a FireWire Adapter Card - Digital Video Editing Kit

StarTech ID: CB1394



This 3 Port PCMCIA IEEE 1394 FireWire 400 Laptop Adapter Card allows you to connect FireWire/i.LINK devices such as iPods or DV (digital video) camcorders to your laptop computer through a CardBus slot.

Compatible with both PC and Mac laptop computers, the adapter card supports hot-swapping FireWire device connections, allowing you to unplug and swap peripherals with ease.

The adapter card includes a 5ft FireWire cable as well as a copy of ULEAD's VideoStudio SE Basic video editing software (Windows only), making it easy to capture and edit video on your notebook computer, directly from your digital video camcorder.

Applications and Solutions

- Digital camcorders (compatible with Sony®, Canon®, Panasonic®, JVC®, Samsung® models)
- Digital cameras
- DVD drives
- External CDR-CDRW drives
- iPods/MP3 players
- Portable hard drives
- Printers
- Scanners

Features

- High speed data transfer rates of up to 400 Mbits/sec.
- Hot swap capabilities allows you to connect or disconnect devices without turning off your laptop
- Includes everything needed to edit your own home movies, add scene transitions and other effects with the included ULEAD® VideoStudio® SE software
- Low power consumption preserves laptop computer battery life

Technical Specifications

- Warranty: Lifetime warranty
- Bus Type: CardBus (PCMCIA)
- Chipset ID: VIA VT6306
- Connector Types: 3 - Firewire 6 pin Female
- Product Height: 1.97 in [5 cm]
- Product Length: 33.7 in [85.6 cm]
- Maximum Data Transfer Rate: 400 Mbps
- Number of Ports: 3
- Carton Quantity: 50
- Industry Standards: IEEE 1394-1995
- Industry Standards: 1394A
- Industry Standards: OHCI
- Shipping (Package) Weight: 0.51 lb [0.23 kg]
- Product Weight: 4.94 oz [140 g]
- Product Width: 2.13 in [5.4 cm]
- Slot Type: 32-bit CardBus Compatible PCMCIA Type II slot
- Connectivity: Up to 63 devices by cascading multiple hubs
- Optional Power Adapter: 12VDC, 1000+ mA, Center Positive
- Power Adapter Included: No
- OS Compatibility: Windows 98SE/ ME/ 2000/ XP(32/64bit)/ 2003(32/64bit)/ Vista(32/64bit)/ 7(32/64bit), Mac OS 8.6 and up, and Linux

