

3 Port CardBus 1394a FireWire Adapter Card - Digital Video Editing Kit

StarTech ID: CB1394



This 3 Port PCMCIA IEEE 1394 FireWire 400 Laptop Adapter Card allows you to connect FireWire/i.LINK devices such as iPods or DV (digital video) camcorders to your laptop computer through a CardBus slot.

Compatible with both PC and Mac laptop computers, the adapter card supports hot-swapping FireWire device connections, allowing you to unplug and swap peripherals with ease.

The adapter card includes a 5ft FireWire cable as well as a copy of ULEAD's VideoStudio SE Basic video editing software (Windows only), making it easy to capture and edit video on your notebook computer, directly from your digital video camcorder.

Applications

- iPods/MP3 players
- Portable hard drives
- External CDR-CDRW drives
- DVD drives
- Digital cameras
- Digital camcorders (compatible with Sony®, Canon®, Panasonic®, JVC®, Samsung® models)
- Scanners
- Printers

Features

- Includes everything needed to edit your own home movies, add scene transitions and other effects with the included ULEAD® VideoStudio® SE software
- High speed data transfer rates of up to 400 Mbits/sec.
- Hot swap capabilities allows you to connect or disconnect devices without turning off your laptop
- Low power consumption preserves laptop computer battery life
- Connect up to 63 devices by cascading multiple hubs

Technical Specifications

Warranty	Lifetime
Ports	3
Interface	FireWire 400 (1394a)
Bus Type	CardBus (PCMCIA)
Industry Standards	1394A
Industry Standards	IEEE 1394-1995
Industry Standards	OHCI
Chipset ID	VIA - VT6306
Connector Type(s)	1 - PC Card (Type II; Cardbus)
Connector Type(s)	3 - Firewire 400 (6 pin; IEEE 1394a) Female
Maximum Data Transfer Rate	400 Mbps
OS Compatibility	Windows 98SE/ ME/ 2000/ XP(32/64bit)/ 2003(32/64bit)/ Vista(32/64bit)/ 7(32/64bit), Mac OS 8.6 and up, and Linux
Product Length	33.7 in [85.6 cm]
Product Width	2.1 in [5.4 cm]
Product Height	2 in [5 cm]
Product Weight	4.9 oz [140 g]
Power Adapter Included	No
Output Voltage	12 DC
Output Current	1A+
Center Tip Polarity	Positive
System and Cable Requirements	32-bit CardBus Compatible PCMCIA Type II slot
Note	Separate power adapter only required if connecting high-powered FireWire device(s) that draw more power than CardBus slot can provide.
Shipping (Package) Weight	0.5 lb [0.2 kg]
Included in Package	1 - CardBus FireWire Card
Included in Package	1 - FireWire 6-pin to 4-pin cable
Included in Package	1 - VideoStudio software CD
Included in Package	1 - Instruction Manual

Certifications, Reports and Compatibility

