

## **1 Port USB 2.0 & 2 Port FireWire ExpressCard Laptop Combo Adapter Card**

*StarTech ID: EC1U2F*



This versatile ExpressCard adapter lets you add two FireWire 400 and one USB 2.0 port to your laptop computer, allowing you to connect popular peripheral devices such as digital cameras, DV camcorders, or virtually any portable media device.

A broadly compatible solution, the ExpressCard adapter is supported by Windows 98SE/ME/2000/XP/64-Bit/Vista operating systems and is backed by StarTech.com's Lifetime Warranty.

### **Applications and Solutions**

- Easily add 2 FireWire and 1 USB 2.0 ports to your notebook computer ExpressCard slot

## Features

- Compliant with ExpressCard / 34mm Type II standard
- Complies with 1394a/1394b and Open Host Controller Interface (OHCI) 1.1/1.2 specifications
- Plug and play, hot-swap device functionality
- Supports FireWire 100/200/400 Mbps transfer rates
- Supports USB transfer rates up to 480 Mbps and USB 1.1 transfer rates up to 12 M
- USB 2.0 and IEEE-1394a compliant

## Technical Specifications

- Warranty: Lifetime warranty
- Bus Type: ExpressCard
- Chipset ID: TI
- Connector Types: 1 - USB B Female
- Connector Types: 2 - FireWire 6 pin Female
- Number of Ports: 2
- Output Current: 1000mA
- Output Voltage: 5 DC
- Plug Type: B
- Power Adapter Included: Optional
- Center Tip Polarity: Positive
- Carton Quantity: 50
- Shipping (Package) Weight: 0.18 lb [0.08 kg]
- Bus Type: ExpressCard
- Form Factor: 34mm
- OS Support: Windows98SE/ME/2000/XP/64-Bit/Vista
- Chipset: TI XIO2200

