

10 ft USB to Parallel Printer Adapter - M/M

StarTech ID: ICUSB128410



This USB to Parallel Printer Adapter allows USB capable PCs to print to any standard parallel printer, converting a USB port into a Centronics (male) connector for direct connection to a parallel printer.

The USB interface provides a much faster data transfer rate than a standard parallel port, thereby reducing the time waiting for a print job to be sent to your printer.

A portable, space-saving solution, the USB to Parallel Printer Adapter is self-powered and provides Plug and Play installation on any USB-compliant computer running Windows 98/ME/2000/XP/Vista.

Applications and Solutions

- Allows you to quickly add a parallel port to your Windows 98SE/ME/2000/XP computer

Features

- Fully Plug & Play for easy installation
- High speed bi-directional parallel port compliant to IEEE-1284 industry standard
- Low power consumption as it draws power from the USB connection
- No IRQ required for installation

Technical Specifications

- Warranty: Lifetime warranty
- Color: Black
- Connector Types: 1 - Centronics 36 Male
- Connector Types: 1 - USB A Male
- Product Length: 72.99 in [1854 mm]
- Operating Temperature: 5°C to 40°C (41°F to 104°F)
- Power Consumption: .90
- Carton Quantity: 120
- Storage Temperature: -20°C to 70°C (-4°F to 158°F)
- Shipping (Package) Weight: 0.75 lb [0.34 kg]
- Cable Length: 3m (10 ft)
- Connectors: USB Type A Male, Centronics 36 Male
- Enclosure: Plastic
- Humidity: 0~80% RH non-condensing
- Power Consumption: 90mA (max)
- Power Mode: Bus powered
- Humidity: 0~80% RH
- OS Compatibility: Windows 98SE/ ME/ 2000/ XP(32/64bit)/ Vista(32/64bit)/ 7(32/64bit)/ Server 2008 R2

